

Caratteristica		Specifiche							
Linea	Modello	Azionamenti DA200A-UL							
1 fase 3 fase 230V	DA200A-	E-2R8-S-2	E-6R0-S-2	C-2R8-S-2	C-6R0-S-2	N-2R8-S-2	N-6R0-S-2	F-2R8-S-2	F-2R8-S-2
I nom.	(A)	2.8	6.0	2.8	6.0	2.8	6.0	2.8	6.0
Motore	(KW)	0.1/0.2/0.4	0.75/1.0	0.1/0.2/0.4	0.75/1.0	0.1/0.2/0.4	0.75/1.0	0.1/0.2/0.4	0.75/1.0
3 fase 230V	DA200A-	E-010-S-2	E-013-S-2	C-010-S-2	C-013-S-2	N-010-S-2	N-013-S-2	F-010-S-2	F-013-S-2
I nom.	(A)	10	13	10	13	10	13	10	13
Motore	(KW)	1.5-2.0	3.0	1.5-2.0	3.0	1.5-2.0	3.0	1.5-2.0	3.0
3 fase 400V	DA200A-	E-1R6-T-2	E-5R5-T-2	C-1R6-T-2	C-5R5-T-2	N-1R6-T-2	N-5R5-T-2	F-1R6-T-2	F-5R5-T-2
I nom.	(A)	1.6	5.5	1.6	5.5	1.6	5.5	1.6	5.5
Motore	(KW)	0.2/0.4	1.0-1.5	0.4	1.0-1.5	0.4	1.0-1.5	0.4	1.0-1.5
3 fase 400V	DA200A-	E-8R5-T2	E-012-T-2	C-8R5-T2	C-012-T-2	N-8R5-T2	N-012-T-2	F-8R5-T2	F-012-T-2
I nom.	(A)	8.5	12	8.5	12	8.5	12	8.5	12
Motore	(KW)	2.0-3.0	4.4	2.0-3.0	4.4	2.0-3.0	4.4	2.0-3.0	4.4
3 fase 400V	DA200A-	E-016-T-2	E-021-T-2	C-016-T-2	C-021-T-2	N-016-T-2	N-021-T-2	F-016-T-2	F-021-T-2
I nom.	(A)	16	21	16	21	16	21	16	21
Motore	(KW)	5.5	7.5	5.5	7.5	5.5	7.5	5.5	7.5
Versioni		Analogica + treno impulsi + RS485		CANopen		EtherCAT		Profinet	
Posizionatore		128 profili integrati o via RS485 Modbus RTU		Riferimento di posizione via Bus					